

SECTION 2.

OPERATION

1. INTRODUCTION

This section provides complete operating information needed for this multi-function counter. This section includes a description of all front panel controls, connectors and indicators, operating instructions, operator's maintenance.

2. PREPARATION FOR USE

1) Power Requirements.

It requires a power source of 115 or 230V AC, 45 to 70Hz single phase. Power consumption is 10 watts maximum.

2) Line Voltage Selection.

Line voltage selection is determined by the position of the line voltage selector switch located on the rear panel. Line voltage is preset at the factory for 115V (90–120V) or 230V (180–250V) as ordered by the customer.